



VERA
MULTIMEDIA

perfect tool to control all kinds of lighting genres

MA Lighting grandMA3 light

TECHNICAL DATA

Parameters	16 384 (HTP/LTP) / 4 096 (Mode2 - HTP/LTP)
Features	Real-time control for up to 250 000 parameters per session 41 rotary RGB backlit encoder; 15 backlit motorized 60 mm faders 60 separate playbacks; 16 assignable x-keys Built-in uninterruptible power supply (UPS)
Connectivity	1x Neutrik powerCON TRUE1 AC; 3x etherCON RJ45 6x 5-pin XLR DMX512-A out; 1x 5-pin XLR DMX512-A in 2x 5-pin DIN MIDI in/out; 1x 3-pin XLR Linear Timecode 1x 3-pin XLR Audio in; 1x Remote; 2x DisplayPort; 2x SPDIF in/out 3x USB-A 3.0; 3x USB-A 2.0; 2x 4-pin XLR Desk light
Power consumption	300 W (maximum)
Thermal	Min. temperature: 0°C; max. temperature: 40°C
Dimensions	854×255×871 mm (W×H×D - maximally unfolded and drawer opened)
Net weight	33 kg net