



lightweight and portable mixer/power amplifier

Yamaha EMX2

TECHNICAL DATA

Channels	10 (4 mono; 3 stereo)
Power	2x 250 W [4 Ω]; 2x 170 W [8 Ω] (1 kHz THD+N <10%) 2x 110 W [4 Ω]; 2x 110 W [8 Ω] (1 kHz THD+N <1%)
Noise	-115 dBu (A-weighted)
Crosstalk	-80 dB (1 kHz; measured with 1 kHz band pass filter)
THD	0.2% (13.8 W; speakers); 0.4% (23.2 W; speakers) 0.05% (+10 dBu; monitor); 0.009% (+20 dBu; monitor)
Connectivity	2x Combo XLR-1/4" (in); 2x XLR (3-pin; in); 6x 1/4" (in) 2x RCA (in); 1x 3.5 mm jack (stereo in); 1x 1/4" (monitor out) 1x 1/4" (subwoofer out); 1x 1/4" (speaker)
Dimensions	375×147×220 mm (W×H×D)
Net weight	4.2 kg net