



compact 18 in / 8 out digital mixer with Wi-Fi

## Allen & Heath CQ-18T

### TECHNICAL DATA

Frequency response	20 Hz - 20 kHz (+0 / -0.5 dB)
Dynamic range	110 dB
Headroom	+18 dB
Latency	<0.7 ms (local mic input to main L/R)
THD+N	0.002% (-92 dBu; USB soundcard; @0 dBu 1 kHz); 0.004% (-88 dBu; USB soundcard; @-30 dBu 1 kHz);
Impedance	>1.5 k $\Omega$ (XLR); >10 k $\Omega$ (TRS)
Power	12V DC; 5A (100-240V AC, 50/60Hz input PSU supplied)
Interface	Wi-Fi 802.11 a/b/g/n/ac; Bluetooth 4.1
Power consumption	35 W
Connectivity	8x XLR (mic/line in); 8x XLR/Jack (combo mic/line in); 1x TRS (footswitch); 2x TRS (stereo in); 6x TRS (out); 2x XLR (main L/R out); 1x RJ45; 1x USB-A 2.0; 1x USB-B 2.0; 1x SD card slot
Dimensions	346×89×242 mm (W×H×D)
Net weight	3 kg net